

# Accent Module

**Latest Firmware Version:** 1.00.09

**Release Date:** December 19, 2018

## Firmware Update Instructions

1. Download the **FW\_update.FUP** firmware update file and place it in the root directory (not in any folder) of a USB flash drive.
2. On the Accent Module, press and hold the **B1, B2 and B3 buttons** simultaneously while powering on the unit.
3. The unit will enter firmware update mode, and show the following message on the display: **Please insert USB drive!**
4. Connect the USB flash drive with the firmware update file to the **USB port** on the rear panel of the Accent Module.
5. The firmware will begin updating automatically. The display will show **Updating** and the percentage complete while the update is in progress.

**Note:** Do not unplug or power off the Accent Module, or remove the USB flash drive, while the update is in progress. Doing so may damage your USB drive.

6. Allow the update process to complete. When the update is complete, the display will show the following message: **Update Successful! Please Reset!**
7. Reset the Accent Module by powering it off and then back on to finalize the update.  
Congratulations—your Accent Module is now using the latest firmware!

## Change History

### Changes Since 1.00.08

- Fixes connection issue with Keystation Mini 32 MK3, Axiom AIR Mini 32, Keystation 49 MK3, Keystation 61 MK3, and Hammer 88.

## Technical Support

For additional help, visit [m-audio.com/support](https://www.m-audio.com/support)